


# EVENT 100C

EVENT 100C is a RGBL LED fresnel light with zoom


# USER MANUAL

CE IP20  
Indoor



REV 1.0 - 24

English Version



# Table of contents

Caution! .....	3
Introduction .....	3
Safety instructions .....	3
Installation.....	4
Read 'Safety information' before installing the fixture.....	4
Fastening the fixture to a flat surface .....	4
Mounting the fixture on a truss .....	4
Securing with a safety cable .....	5
Occupation of the XLR-connection .....	5
Building a serial DMX-chain .....	5
DMX-512 connection with DMX terminator .....	5
Power connection .....	5
Control Menu Map .....	6
DMX Protocol.....	6
Fixture Cleaning .....	8
Troubleshooting .....	9
Technical specifications.....	9

## Caution!



Be careful with your operations. With a dangerous voltage you can suffer a dangerous electric shock when touching the wires!



Avoid looking directly into the light source!

Wear protective glasses and other PPE (personal protective equipment) when working on or near the fixture.



Always make sure you are connecting this product to the proper voltage in accordance with the specifications in this manual or on the product's specification label. Make sure it is grounded when using it!

Unplug mains lead before opening the housing!

Make sure that the power cord is never crimped or damaged by sharp edges. Check the fixture and the powercord from time to time.

Make sure to replace the fuse with another of the same type and rating.



For your own safety, please read this user manual carefully before you initial start-up.

Follow operating safety precautions and pay attention to warning signs methods and equipment on the user manual.



Warning! This symbol indicates a hot surface. Certain parts of the housing can become hot during operation. After use, wait for a cool-down period of at least 10 minutes before handling or transporting the device.



T = 45°C

Indoor use only! To prevent risk of fire or shock, do not expose this product to rain or moisture. IP 20 rating.

The ambient temperature must always be between -5° C and +45° C.

Every person involved with the installation, operation and maintenance of this device has to

- be qualified
- follow the instructions of this manual
- consider this manual to be part of the total product
- keep this manual for the entire service life of the product
- pass this manual on to every further owner or user of the product
- download the latest version of the user manual from the Internet

## Introduction

Thank you for having chosen EVENT 100C. You will see you acquired a powerful and versatile device. Unpack your item. Before you initial start-up, please make sure that there is no damage caused by transportation. Should there be any, consult your dealer and do not use the device.

## Safety instructions

This device has left our premises in absolutely perfect condition. In order to maintain this con-

# EVENT 100C

---

dition and to ensure a safe operation, it is absolutely necessary for the user to follow the safety instructions and warning notes written in this user manual. Always disconnect from the mains, when the device is not in use or before cleaning it. Keep away children and amateurs from the device! There are no serviceable parts inside the device. Maintenance and service operations are only to be carried out by authorized dealers.

## Installation

Read 'Safety information' before installing the fixture.

The fixture is designed for indoor use only and must be used in a dry location with adequate ventilation. Ensure that none of the fixture's ventilation slots are blocked.

Fasten the fixture to a secure structure or surface. Do not stand it on a surface or leave it where it can be moved or fall over. If you install the fixture in a location where it may cause injury or damage if it falls, secure it as directed in this user manual using a securely anchored safety cable that will hold the fixture if the primary fastening method fails.


### Fastening the fixture to a flat surface

The fixture can be fastened to a hard, fixed, flat surface that is oriented at any angle. Ensure that the surface and all fasteners used can support at least 10 times the weight of all fixtures and equipment to be installed on it.

Fasten the fixture securely. Do not stand it on a surface or leave it where it can be moved or fall over. If you install the fixture in a location where it may cause injury or damage if it falls, secure it as directed below with a securely anchored safety cable that will hold the fixture if the primary fastening method fails.

### Mounting the fixture on a truss

The fixture can be clamped to a truss or similar rigging structure in any orientation. When installing the fixture hanging vertically down, you can use an open-type clamp such as a G-clamp. When installing in any other orientation, you must use a half-coupler clamp that completely encircles the truss chord.



To clamp the fixture to a truss:

1. Check that the rigging structure can support at least 10 times the weight of all fixtures and equipment to be installed on it.
2. Block access under the work area.
3. Fold the legs of the mounting bracket together and bolt a rigging clamp securely to the mounting bracket. The bolt used must be M10. It must pass through both mounting bracket legs and be fastened with a self-locking nut.
4. Working from a stable platform, hang the fixture with its clamp on the truss and fasten the clamp securely.


5. Secure the fixture with a safety cable as directed below.

## Securing with a safety cable

Secure the fixture with a safety cable (or other secondary attachment) that is approved for the weight of the fixture so that the safety cable will hold the fixture if a primary attachment fails.

Loop the safety cable through the eyebolt in the back of the fixture and around a secure anchoring point. Do not loop the safety cable around the fixture's mounting bracket only, as this will leave the fixture unsecured if it separates from the bracket.

Occupation of the XLR-connection:



If you are using controllers with this occupation, you can connect the DMX-output of the controller directly with the DMX-input of the first fixture in the DMX-chain. If you wish to connect DMX-controllers with other XLR-outputs, you need to use adapter-cables.

## Building a serial DMX-chain:

Connect the DMX-output of the first fixture in the DMX-chain with the DMX-input of the next fixture.

Always connect one output with the input of the next fixture until all fixtures are connected.

## DMX-512 connection with DMX terminator:

For installations where the DMX cable has to run a long distance or is in an electrically noisy environment, such as in a discotheque, it is recommended to use a DMX terminator. This helps in preventing corruption of the digital control signal by electrical noise. The DMX terminator is simply an XLR plug with a 120 resistor connected between pins 2 and 3, which is then plugged into the output XLR socket of the last fixture in the chain.

**Caution:** At the last fixture, the DMX-cable has to be terminated with a terminator. Solder a 120  $\Omega$  resistor between Signal (-) and Signal (+) into a 3-pin XLR-plug and plug it in the DMX-output of the last fixture.

## Power connection

### Power Requirements


The EVENT 100C luminaire operates on 100 to 240 volts AC (+/- 10%, auto-ranging). The luminaire contains an auto-ranging power supply.

# EVENT 100C

Connection with the mains:

Connect the device to the mains with the enclosed power supply cable.

The occupation of the connection cables as below:

Cable color	Connection	International
<b>Brown</b>	<b>Live</b>	<b>L</b>
<b>Blue</b>	<b>Neutral</b>	<b>N</b>
<b>Yellow/green</b>	<b>Earth(Ground)</b>	

## Control Menu Map

Menu	Sub menu	Operation
Addr	d001-d512	RDM/DMX address
CHnL	3CH	Channel mode
	4CH	
	5CH	
	6CH	
	11CH	
SP--	T.(00-99)	Auto program speed increasing
Pr--	Pr01~Pr10	Auto program
CoLo	C.(01~15)	Color preset
Strb	S.00-S.20	Strobr with speed in creasing
rL--	r.(000-255)	red dimmer
gL--	g.(000-255)	green dimmer
bL--	b.(000-255)	blue dimmer
uL--	u.(000-255)	lime dimmer
nodE	nod.0	Dimmer speed 0 (no delay)
	nod.1	Dimmer speed 1
	nod.2	Dimmer speed 2
	nod.3	Dimmer speed 3
	nod.4	Dimmer speed 4 (slowest speed)
ld	ld.01-ld.66	IDaddress setting
tEnP	-25~100	Fixture temperature
UEm		Firmw are version
rSEt	yes/no	Reset
pnnF	(1.2~24.0)F	PWM refresh rate adjustment (KHz)

## DMX Protocol

### ARC.1

3 Channels Mode	Function	Function Control
CH1	Red	000-255: 0-100% Red dimmer
CH2	Green	000-255: 0-100% Green dimmer
CH3	Blue	000-255: 0-100% Blue dimmer

**AR1.D**

4 Channels Mode	Function	Function Control
CH1	Dimmer	000-255: 0-100% dimmer
CH2	Red	000-255: 0-100% Red dimmer
CH3	Green	000-255: 0-100% Green dimmer
CH4	Blue	000-255: 0-100% Blue dimmer

**ARC.2**

4 Channels Mode	Function	Function Control
CH1	Red	000-255: 0-100% Red dimmer
CH2	Green	000-255: 0-100% Green dimmer
CH3	Blue	000-255: 0-100% Blue dimmer
CH4	Lime	000-255: 0-100% Lime dimmer

**AR2.D**

5 Channels Mode	Function	Function Control
CH1	Dimmer	000-255: 0-100% dimmer
CH2	Red	000-255: 0-100% Red dimmer
CH3	Green	000-255: 0-100% Green dimmer
CH4	Blue	000-255: 0-100% Blue dimmer
CH5	Lime	000-255: 0-100% Lime dimmer

**AR2.S**

6 Channels Mode	Function	Function Control
CH1	Dimmer	000-255: 0-100% dimmer
CH2	Red	000-255: 0-100% Red dimmer
CH3	Green	000-255: 0-100% Green dimmer
CH4	Blue	000-255: 0-100% Blue dimmer
CH5	Lime	000-255: 0-100% Lime dimmer
CH6	Strobe	000-255: Strobe with speed increasing

**STAG**

11 Channels Mode	Function	Function Control
CH1	Dimmer	000-255: 0-100% dimmer
CH2	Red	000-255: 0-100% Red dimmer
CH3	Green	000-255: 0-100% Green dimmer
CH4	Blue	000-255: 0-100% Blue dimmer
CH5	Lime	000-255: 0-100% Lime dimmer

# EVENT 100C

11 Channels Mode	Function	Function Control
CH6	Color preset & color temp	000-010:No function
		011-030:Red100%, Green 0-100%, Blue 0%
		031-050:Red100-0%, Green100%, Blue 0%
		051-070:Red 0%, Green 100%, Blue 0-100%
		071-090:Red 0%, Green 100-0%, Blue 100%
		091-110:Red 0-100%, Green 0%, Blue 100%
		111-130:Red 100%, Green 0%, Blue 100%
		131-150:Red 100%, Green 0-100%, Blue 0-100%
		151-170:Red 100-0%, Green 100-0%, Blue 100%
		171-200:Red 100%, Green 100%, Blue 100%
		201-220:Colour temperature 1
		220-255:Colour temperature 2
CH7	Strobe	000-013: Strobe off
		014-255: Strobe wttth speed increasing
CH8	Auto program	000-020: no function
		021-030: Auto 1
		031-040: Auto 2
		041-050: Auto 3
		051-060: Auto 4
		061-070: Auto 5
		071-080: Auto 6
		081-090: Auto 7
		091-100: Auto 8
		101-110: Auto 9
		111-120: Auto 10
		121-255: no function
CH9	Auto program speed	000-255: Speed increasing
CH10	Auto program speed	000-255: Dimmer speed 0-4
CH11	ID address setting	000-255: ID1-ID66

## HSV

3 Channels Mode	Function	Function Control
CH1	Hue	000-255: 0-100% Hue
CH2	Saturation	000-255: 0-100% Saturation
CH3	Valur (brightness)	000-255: 0-100% Valur (brightness)

## Fixture Cleaning

Due to fog residue, smoke, and dust cleaning the internal and external optical lenses and mirror should be carried out periodically to optimize light output. Cleaning frequency depends on the environment in which the fixture operates (I.e. smoke, fog residue, dust, dew). In heavy club use we recommend cleaning on a monthly basis. Periodic cleaning will ensure longevity, and crisp output.



To clean the fixture:

1. Disconnect the fixture from power and allow it to cool for at least 10 minutes.
2. Vacuum or gently blow away dust and loose particles from the outside of the fixture with low-pressure compressed air.
3. Clean the surfaces by wiping gently with a soft, clean lint-free cloth moistened with a weak detergent solution. Do not rub glass surfaces hard: lift particles off with a soft repeated press. Dry with a soft, clean, lint-free cloth or low-pressure compressed air. Remove stuck particles with an unscented tissue or cotton swab moistened with glass cleaner or distilled water.
4. Check that the fixture is dry before reapplying power.

## Troubleshooting

Listed below are a few common problems that you may encounter, with solutions.

The fixture does not work, no light

- Check the connection of power and main fuse. Be sure the external fuse has not blown.
- Measure the mains voltage on the main connector.

## Technical specifications

Model	EVENT 100C
Power supply:	AC100-240V, 50/60Hz
Light source:	250W LED
Color:	RGBL
Zoom range:	25° - 60° manual zoom
Power connection:	Dedicated power in
Signal connection:	3-pin XLR in & out
Control channels:	ARC.1(3CH), AR1.D(4CH), ARC.2(4CH), AR2.D(5CH), AR2.S(6CH), HSV(3CH), STAG(11CH)
Control mode:	Rotary, DMX, RDM
Housing:	Color black, engineering plastic
Size:	403 x 180 x 124mm
N.W.:	2.5 kg
Accessories(incl.)	Power cable, barndoor, gel frame, Safety rope
Accessories(opt.):	Clamp
Environment:	IP 20

Please note: All information is subject to change without prior notice.